

group is taken out. (4xM4 Countersunk Bolt)

Note: It is tightened with 3Nm torque while remounting the lighting group.

The cables coming to the connectors from the lighting group are removed..

Note: When installing the cable, the connector bolts are tightened with 1.5Nm.

8. The cables coming from the LED driver to the connectors are removed

Note: When installing the cable, the connector bolts are tightened with 1.5Nm.

9. Bolts that fix the LED driver sheet to the bollard are removed. (2xM4 Flat Head Screws)

Note: During the reinstallation of the LED Driver sheet 1.5 Nm torque must be applied.

10. The bolts fixing the LED driver to the LED driver sheet are removed. LED driver is taken out. (2 M3 Flat Head Screws)

Note: When installing the LED driver sheet 1.5 Nm torque must be applied.

:\$1,16\$5(0\$.6)25,167\$,21

\$0\$7(1\$&

