

Staircase lighting switches and timers

Tactile push buttons PULSATEMP

- These articles cover both functions, push button + timer.
- Very useful to replace directly any switch by and temporize the light at once.
- Tactile control with 2 & 3 wire installation models.
- Flush and surface models.
- Mounting by clamps or screws.

CLAMPS mounting models




- Mounting by clamps.
- Can be mounted into any type of universal mechanism box.
- White color.

Technical Specifications

REFERENCE		PT GAR EL1	PT GAR 001
Model		Flush mounting in standard box with CLAMPS	
Supply Voltage		230V~ 50Hz	
Load Capacity	Installation	3-wire	2-wire
	LED lamps	400W	Not valid
	Incandescent lamps	3000W	40W - 500W
	230 Halogen lamps	3000W	40W - 500W
	LV Halogen lamps with inductive transfo	2400W	50W - 400W
	LV Halogen lamps with electronic transfo	3000W	40W - 500W (L-type)
	Compensated Fluorescence	1300W (130μF)	Not valid
	CFL lamps	18 x 7W; 12 x 11W; 10 x 23W	Not valid
	Motors	200VA	36W - 100VA
Time settings		30sec ~ 10min	

Dimensions



Wiring Diagrams

