



**Manufacturer:**

Seikoh Giken

**Product Name:**

Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector,  
Singlemode, APC, 126µm (micron) Ferrule Hole Size

**Manufacturer Part Number:**

LCNZ-1A14126001G



Learn More

▶ [Click here for more details on the Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm \(micron\) Ferrule Hole Size](#)

DOCUMENT NUMBER S05-H515-03E

# LCNZ-1A14 Series

ø 1.25 mm Single mode

Zirconia FERRULE

- for LC-APC Connector -

## TECHNICAL SPECIFICATIONS



**SEIKOH GIKEN**

**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

[focenter.com](http://focenter.com) • 508-992-6464 | (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

23 Centre Street • New Bedford, MA 02740 USA

Product specifications and data are subject to change without notice. FOC last update 3/11/2026.



**Manufacturer:**

Seikoh Giken

**Product Name:**

Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

**Manufacturer Part Number:**

LCNZ-1A14126001G



▶ [Click here for more details on the Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm \(micron\) Ferrule Hole Size](#)

**S05-H515-03E  
LCNZ-1A14 Series**

LCNZ-1A14 Series ø 1.25 mm Single mode Zirconia FERRULE  
- for LC-APC Connector -  
TECHNICAL SPECIFICATIONS

ACD-1NA4-01	November	2001
ACD-1NA4-02	March	2004
S05-H515-01E	May	2007
S05-H515-02E	June	2007
S05-H515-03E	September	2007

Copyright © 2001 - 2007 by **SEIKOH GIKEN Co.,Ltd.**  
All right reserved.

The information contained herein shall not be reproduced or disclosed to any third party without the express written consent of SEIKOH GIKEN Co., Ltd.  
The specifications contained herein are subject to change without notice.




**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

[focenter.com](http://focenter.com) • 508-992-6464 | (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

23 Centre Street • New Bedford, MA 02740 USA

Product specifications and data are subject to change without notice. FOC last update 3/11/2026.



**Manufacturer:**

Seikoh Giken

**Product Name:**

Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

**Manufacturer Part Number:**

LCNZ-1A14126001G



Learn More

▶ Click here for more details on the Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

S05-H515-03E  
LCNZ-1A14 Series

TABLE OF CONTENTS

Section	Page
1 SCOPE	1
2 PART NUMBER	1
3 GENERAL SPECIFICATIONS	2
3.1 Physical Dimensions	2
3.2 Appearance	2
4 SHIPPING INSPECTION	2
5 PACKING	2
6 IDENTIFICATION	2
7 HANDLING AND CARE	2
7.1 Conditions of Storage	2
7.2 Precautions of Use	2
7.3 Disposal	2

Table


Table 1	Part Number	1
---------	-------------	---

Contact the professionals at Fiber Optic Center for a quote or to get more details.

[focenter.com](http://focenter.com) • 508-992-6464 | (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

23 Centre Street • New Bedford, MA 02740 USA

Product specifications and data are subject to change without notice. FOC last update 3/11/2026.



**Manufacturer:**

Seikoh Giken

**Product Name:**

Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

**Manufacturer Part Number:**

LCNZ-1A14126001G



▶ Click here for more details on the Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

**S05-H515-03E  
LCNZ-1A14 Series**

1 SCOPE

These specifications apply to the LCNZ-1A14 series ø 1.25 mm single mode zirconia ferrule - for LC-APC connector - supplied by SEIKOH GIKEN Co., Ltd.

2 PART NUMBER

Part number of the ferrule is shown in Table 1.

Table 1 Part Number

MODEL Number	TYPE Number								
<b>LCNZ-1A</b>	<b>1</b>	<b>4</b>	<b>1</b>	<b>2</b>	<b>5</b>	<b>0</b>	<b>0</b>	<b>1</b>	<b>G</b>
	Flange Shape		Ferrule I.D. [µm]			Auxiliary digit			
	1 4	Standard	1 2 5	ø 125	1 2 F	ø 125.5	0 0 1 G		
			1 2 6	ø 126					

Please contact us for availability of other specifications.

**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

[focenter.com](http://focenter.com) • 508-992-6464 | (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

23 Centre Street • New Bedford, MA 02740 USA

Product specifications and data are subject to change without notice. FOC last update 3/11/2026.



**Manufacturer:**

Seikoh Giken

**Product Name:**

Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm (micron) Ferrule Hole Size

**Manufacturer Part Number:**

LCNZ-1A14126001G



▶ [Click here for more details on the Seikoh Giken 1.25mm Zirconia Ferrule for LC Connector, Singlemode, APC, 126µm \(micron\) Ferrule Hole Size](#)

**S05-H515-03E  
LCNZ-1A14 Series**

**3 GENERAL SPECIFICATIONS**

**3.1 Physical Dimensions**

Physical dimensions should comply with the drawing attached.

**3.2 Appearance**

There should be no remarkable burr, peeling of plating or scratches.

**4 SHIPPING INSPECTION**

The ferrule outer diameter, ferrule hole diameter, concentricity of ferrule hole diameter, mating length and appearance are inspected before shipping and the inspection results are enclosed.

**5 PACKING**

The product is packed to prevent damage during shipment.

**6 IDENTIFICATION**

Identification label should indicate the part number and the lot number of the product(s) and should be permanently attached to the packing bag.

**7 HANDLING AND CARE**

**7.1 Conditions of Storage**

Keep the product, in the packing bag, at the following conditions for its storage|

- Storage temperature: -40 to +85 degrees C
- Storage humidity: 0 to 85%RH, non-condensing

**7.2 Precautions for Use**

Contamination, oil, sweat and others debris on the ferrule end face may influence the performance of the product. If contamination is on the ferrule end face, wipe the end face with the end face cleaner.

**7.3 Disposal**

When discarding this product, please follow the regulations of your own country.

**Contact the professionals at Fiber Optic Center for a quote or to get more details.**

[focenter.com](http://focenter.com) • 508-992-6464 | (800) 473-4237 • [sales@focenter.com](mailto:sales@focenter.com)

23 Centre Street • New Bedford, MA 02740 USA

Product specifications and data are subject to change without notice. FOC last update 3/11/2026.