IR Remote Control for Constant Light Controllers

Description

- IR remote control for setting and controlling the constant light control devices.
- Its main function is the programming of these systems without having to access to the ceiling.
- In addition, it allows a manual control (on/off and dimming) of the lighting connected to this type of devices.
- IR communication, therefore, with an only remote control it is possible to adjust all the devices of an installation.



Technical Specifications

Reference	CO REG R05
Power supply	1 battery 3V CR2032 (included)
Battery useful life	>4 years
Infrareds	Focussed and low range transmission (2-3m)
Compatible with	RE DMS 001, RE DMS DA1, RE DMS 003, RE DMS
	DA3, RE DMS 004, RE DMS DA4
Working temperature	0ºC ~ +45ºC
Protection degree	IP51 according to EN60529
Dimensions	105 x 50 x 12mm
According to the Standard	EN60730

