

# TI URA R00

## Uranus Battery-Operated Doorbell-Receiver



- Battery-operated doorbell receiver for wall mounting.
- Can be installed with two wired 230V push buttons and/or wireless push buttons or transmitters.
- Range: 200m (open field).
- Power supply: 3 x 1.5V R6 batteries (not included).
- 32 different melodies to choose from.
- 4 volume levels.
- Color: White cover and black base.

REFERENCE	TI URA R00
Supply voltage	3 batteries x 1,5V type R6
Communication	RF
Frequency	868MHz
Scope	200m (open field)
Volume	4 levels
Melodies	32 melodies
Colour	White cover and back base
Sound level	75dB
Installation	On wall
Dimensions	104 x 170 x 45mm
Protection degree	IP20